# Observing geometry effects on a GNSS based water vapor tomography solved by Least Squares and by Compressive Sensing

Marion Heublein<sup>1</sup>, Patrick Erik Bradley<sup>1</sup>, and Stefan Hinz<sup>1</sup>

<sup>1</sup>Karlsruhe Institute of Technology, Institute of Photogrammetry and Remote Sensing, 76128 Karlsruhe, Germany

**Correspondence:** Marion Heublein (marion.heublein@kit.edu)

**Abstract.** In this work, the effect of the observing geometry on the tomographic reconstruction quality of both a regularized Least Squares (LSQ) and a Compressive Sensing (CS) approach for water vapor tomography is compared based on synthetic Global Navigation Satellite System (GNSS) Slant Wet Delay (SWD) estimates. In this context, the term observing geometry mainly refers to the number of GNSS sites situated within a specific study area subdivided into a certain number of volumetric pixels (voxels) and to the number of signal directions available at each GNSS site. The novelties of this research are 1) the comparison of the observing geometry's effects on the tomographic reconstruction accuracy when using LSO resp. CS for the solution of the tomographic system and 2) the investigation of the effect of the signal directions' variability on the tomographic 8 reconstruction. The tomographic reconstruction is performed based on synthetic SWD data sets generated, for many samples of various observing geometry settings, based on wet refractivity information from the Weather Research and Forecasting 10 (WRF) model. The validation of the achieved results focuses on a comparison of the refractivity estimates with the input WRF refractivities. The results show that the recommendation of Champollion et al. (2004) to discretize the analyzed study area into 11 voxels with horizontal sizes comparable to the mean GNSS inter site distance represents a good rule of thumb for both LSO 12 and CS based tomography solutions. In addition, this research shows that CS needs a variety of at least 15 signal directions per site in order to estimate the refractivity field more accurately and more precisely than LSQ. Therefore, the use of CS is

## 17 1 Introduction

are available.

15 16

18 In this paper, we intend to determine the atmospheric water vapor distribution in 3D for each point in time. This adds fur-19 ther essential information to the spatio-temporal analyses of 2D water vapor fields commonly used in weather forcasting and

particularly recommended for water vapor tomography applications for which a high number of multi-GNSS SWD estimates

20 climate research. In addition, atmospheric water vapor delays the microwave signal propagation within the atmosphere and

21 thus represents an error source in e.g. Global Navigation Satellite Systems (GNSS) and Interferometric Synthetic Aperture

22 Radar (SAR) (InSAR) observations. Therefore, a precise knowledge of the water vapor field e.g. is required for accurate de-

formation monitoring using InSAR (Hansen and Yu (2001)). However, the atmospheric water vapor distribution is difficult to

24 model because it is highly variable in time and space. Several approaches exist for reconstructing the three dimensional (3D)

25 tomographic water vapor reconstruction using one dimensional (1D) GNSS SWDs, see Section 2.

One of the main limiting factors in water vapor tomographies consists in the point-wise GNSS observing geometry, which 1 causes an ill-conditioned inverse tomographic model that needs to be regularized. Yet, even after regularization, the observing 2 geometry composed e.g. of the number and the geographic distribution of the GNSS sites, the SWD signal directions, and the 3 voxel discretization still effects the quality of the tomographic solution. This work therefore meets the challenge of comparing 4 the observing geometry's effect on a GNSS based water vapor tomography solved by means of Least Squares (LSQ) resp. by 5 6 means of Compressive Sensing (CS). By investigating the observing geometry's effect on the LSQ and CS solution strategies, 7 the differences between the LSO solution and a CS solution approach benefiting of the signal's sparsity in an appropriate trans-8 form domain for regularization are better understood and recommendations can be given for future water vapor tomography 9 campaigns and the processing of their measurements. Based on synthetic data sets deduced from the Weather Research and Forecasting Model (WRF) described in Skamarock et al. (2005), the presented work answers the research questions 1) in how 10 far the rule of thumb of Champollion et al. (2004), derived for LSQ and recommending a voxel size corresponding to the mean 11 GNSS inter site distance, can be transferred from a LSQ solution to a CS solution. In addition, this research investigates 2) in 12 13 which settings CS is able to more accurately and more precisely reconstruct the tomographic water vapor field than LSO and 3) to which extent multi-GNSS SWD observations improve the tomographic solution obtained by means of LSQ resp. CS, when 14 compared to solutions obtained from SWDs originating from the Global Positioning System (GPS) only. 15

#### 2 Related work

16

32

33

Current water vapor tomographies can be distinguished e.g. based on the methodology and the data sets applied for solving 17 the tomographic model. The tomographic model is commonly established based on the directions along which space-geodetic 18 SWD estimates are acquired and based on a discretization of the investigated atmospheric volume into volumetric pixels (vox-19 20 els) e.g. of constant refractivity. The existing tomography solution approaches applied to such a discretized atmosphere are 21 subdivided into iterative and non-iterative techniques. Bender et al. (2011a) propose different iterative Algebraic Reconstruction Techniques (ART), while Hirahara (2000), Flores et al. (2000), Champollion et al. (2004), Troller (2004), Song et al. 22 23 (2006), Notarpietro et al. (2008), and Rohm (2013) apply different non-iterative methods for solving the tomographic system using a LSQ adjustment. Thanks to its good capability to estimate dynamically changing parameters, Flores et al. (2000), Grad-24 25 inarsky and Jarlemark (2004), and Rohm et al. (2014) choose a Kalman filter approach. Hirahara (2000) proposes a damped 26 least squares solution known from seismic tomography to solve the tomographic problem. Xia et al. (2013) combine iterative and non-iterative techniques. Instead of using voxels in water vapor tomographies with a small number of GNSS sites, Ding 27 et al. (2018) discretize the tomographic field based on the perimeter of the tomographic boundary on the plane and based on 28 meshing techniques. They then determine tomographic fields by means fitting the real distribution of GNSS signals on different 29 tomographic planes at different tomographic epochs. 30 31 In addition to slant wet delay estimates from GNSS, Hurter and Maier (2013) introduce wet refractivity profiles from radio

occultation and radiosonde observations into a combined least squares collocation. Rather than using slant wet delay estimates

as input observations, Nilsson and Elgered (2007) apply a solution that relies directly on GPS phase observations.

equations is usually ill-posed and needs to be regularized e.g. i) by constraining the tomographic system by means of pseudo 2 observations, ii) by introducing additional observations from models, from simulations, or from other sensors, or iii) by de-3 creasing the amount of voxels crossed by no rays at all. Both Flores et al. (2000) and Gradinarsky and Jarlemark (2004) regularize the solution by means of adding horizontal and 5 6 vertical smoothing constraints to the tomographic system and by means of introducing a boundary constraint assuming the refractivity to approach zero above a certain height. Alternatively, as proposed in Elosegui et al. (1998), the refractivity field can 7 8 be assumed to decrease exponentially with increasing height. Yet, while regularizing the solution significantly, both geometric 9 constraints and the exponential decay usually are not able to accurately model the real atmospheric state. As an alternative to using horizontal and vertical constraints relying on physical approximations to the atmospheric behavior, the work in Heublein 10 et al. (2018) and Heublein (2019) exploit the signal's sparsity in a particular, predefined transform domain as prior knowledge 11 for regularizing the tomographic system in order to then reconstruct the signal using an  $L_1$ -norm minimization. Similarly, CS 12 13 and sparse reconstruction are applied here for the tomographic reconstruction of the 3D water vapor field and the CS solution to water vapor tomography is compared to a solution obtained using a classical LSQ approach. Initially presented by Can-14 dès et al. (2006), Donoho (2006), Baraniuk (2007), and Candès and Wakin (2008) for the image or signal recovery from a 15 number of samples below the desired resolution or the Nyquist rate, CS has been, since then, applied to many remote sensing 16 problems in which sparse signals occur. E.g. Potter et al. (2010) and Alonso et al. (2010) describe the use of CS for SAR 17 imaging, Pruente (2010) applies CS for ground moving target identification, Zhu and Bamler (2010), Budillon et al. (2011), 18 19 Aguilera et al. (2013), and Zhu and Bamler (2014) apply CS to SAR tomography, and Li and Yang (2011), Zhu and Bamler (2013), Grohnfeldt et al. (2013), Jiang et al. (2014), and Zhu et al. (2016) use CS for pan-sharpening and hyperspectral image 20 21 enhancement. When compared to classical LSQ adjustments usually applying  $L_2$ -norm regularizations, Compressive Sensing and sparse reconstruction based on a small number of measurements led to promising results. 22 23 However, Compressive Sensing only yields encouraging results if the input data acquisition – corresponding, in water vapor tomography, to the determination of SWD estimates – fulfills certain prerequisites. For general applications of CS, Rauhut 24 25 (2010) e.g. states that randomness in the acquisition step helps to utilizing the minimum number of measurements. When reconstructing images based on frequency data, e.g. Candès et al. (2006) alternatively recommend to randomly measure fre-26 27 quency coefficients such that sparse objects are sensed by taking as few measurements as possible. For CS-based water vapor tomography approaches, no explicit requirements for the SWD acquisition or for designing advantageous observing geometry 28 settings have been established so far. 29 For LSQ, Champollion et al. (2004) state that the optimal horizontal size of a voxel should correspond to the mean inter-site 30 31 distance between the used GNSS sites. Given a certain cutoff elevation angle, the height layers' thicknesses in their approach 32 should be defined such that signals received at a GNSS site situated within a voxel's center are able to cross neighboring voxels. Due to the small wet refractivity values in the upper layers and in order to make the tomographic solutions less sensitive to 33 errors in the input data, Rohm (2012) recommends to increase the height layer thicknesses with increasing altitude. Bender and 34 Raabe (2007) resp. Bender et al. (2009) estimate the spatial distribution of the geometric intersection points between different 35

Independently of the reconstruction strategy, due to the point-wise GNSS observing geometry, the tomographic system of

1

- 1 ray paths in order to compute the information density contained in a given set of GPS signals. They then use this information
- 2 as a precondition to an optimal tomographic reconstruction resp. in order to identify regions that are well covered by GPS
- 3 slant paths. Although Bender et al. (2011b) and Zhao et al. (2019) state that changing the observing geometry by combining
- 4 multi-GNSS observations instead of GPS only observations does not substantially improve the reconstruction quality, Rohm
- 5 (2012) realizes that the uncertainty of the tomographic solution is largely influenced by the mathematical properties of the
- 6 design matrix, depending itself on the observing geometry. With the aim of giving advice for the installation of new permanent
- 7 sites and for the solution of future water vapor tomographies, this work therefore investigates the observing geometry's effect
- 8 on the quality of both a LSQ and a CS solution to the tomographic system.

## 9 3 Methodology

- 10 In order to analyze the observing geometry's effect on the quality of the LSQ and CS solution to water vapor tomography,
- 11 different observing geometry settings are defined. Based on synthetic SWD estimates derived from WRF, 3D water vapor
- 12 distributions are reconstructed for each of the defined observing geometry settings using both LSQ and CS. The quality of the
- 13 LSQ and CS solutions to water vapor tomography is then compared w.r.t. the respective observing geometry settings.

#### 14 3.1 Tomographic model

15 For tomography using GNSS SWDs, Flores et al. (2000) introduce the functional model

16 
$$\operatorname{SWD}_{i,\operatorname{cont}} = 10^{-6} \cdot \int_{\operatorname{SD}_i} N_{\operatorname{wet}} \, \mathrm{d}l,$$
 (1)

- 17 where SWD<sub>i, cont</sub> stands for the integrated slant wet delay observations between a certain satellite and a certain GNSS site and
- 18 dl is a differential along the slant ray path. As in Heublein et al. (2018) and Heublein (2019), the variable  $sp_i$  is the ith slant
- 19 ray path, i.e. the slant ray path of the radiowave signal between a certain satellite and a certain receiver. The variable  $N_{
  m wet}$
- 20 contains the wet refractivity along this path. The index i attains the values

21 
$$i \in \mathbb{N} \text{ with } 1 \le i \le N,$$
 (2)

- 22 where N corresponds to the number of observations available between any receiver and any satellite. When tomographically
- 23 reconstructing the wet refractivity, however, the continuous functional model from Equation 1 is usually replaced by a discrete
- 24 functional model

25 SWD<sub>i,disc</sub> = 
$$10^{-6} \cdot \sum_{j=1}^{L} N_{\text{wet } j} \cdot d_{ij}$$
. (3)

- That is, the 3D water vapor distribution is discretized into  $L = \mathcal{P} \times \mathcal{Q} \times \mathcal{K}$  voxels in longitude, latitude, and height, assuming a
- 27 constant refractivity value for each voxel. As in Heublein et al. (2018) and Heublein (2019), in this work, a uniform voxel dis-
- 28 cretization is selected in the horizontal directions, while the voxel sizes in the vertical direction increase with increasing height.

- 1 Horizontally, the voxels are limited by constant longitudes and latitudes. In the vertical direction, the voxels are separated by
- 2 layers of constant ellipsoidal height.
- As in Heublein et al. (2018) and Heublein (2019), summarizing all observations  $SWD_{i, disc}$  in an observation vector  $y_{data} \in$
- 4  $\mathbb{R}^{N\times 1}$ , all unknown refractivities  $N_{\text{wet } j}$  for

5 
$$j \in \mathbb{N}$$
 with  $1 < j < L$  (4)

- 6 in a parameter vector  $x \in \mathbb{R}^{L \times 1}$ , and all distances  $d_{ij}$  in a design matrix  $\Phi_{\text{data}} \in \mathbb{R}^{N \times L}$ , the discrete tomographic system from
- 7 Equation 3 can be rewritten as

8 
$$y_{\text{data}} = \Phi_{\text{data}} \cdot x$$
 (5)

9 with

10 
$$\Phi_{\text{data}}(i,j) = \begin{cases} d_{ij} & \text{if signal } i \text{ crosses voxel } j \\ 0 & \text{otherwise.} \end{cases}$$
 (6)

- 11 As each signal only passes a small subsection of the study area, most entries of the matrix  $\Phi_{\rm data}$  are zero and only a few matrix
- 12 elements are non-zero (e.g. only about 5% of the entries of  $\Phi_{\rm data}$  are non-zero in the case of an about  $95\times99\,{\rm km}^2$  large study
- 13 area subdivided into  $5 \times 5 \times 5$  voxels, disposing of seven GNSS sites and ten signals per site). For voxels that are not crossed by
- 14 any signals,  $\Phi_{\text{data}}$  has a zero column. Therefore, the tomographic model and the mathematical properties of the design matrix
- 15 largely depend on the observing geometry settings described in Section 3.3.

#### 16 3.2 Solution of the inverse tomographic model using LSO resp. CS

17 The LSQ solution to Equation 5 is derived by solving the minimization problem

18 
$$\hat{\boldsymbol{x}} = \underset{\boldsymbol{x}}{\operatorname{argmin}} \left\{ \underbrace{\|\boldsymbol{y}_{\text{data}} - \boldsymbol{\varPhi}_{\text{data}} \cdot \boldsymbol{x}\|_{2}^{2}}_{\text{data fidelity term}} + \underbrace{\sum_{t=1}^{3} \Gamma_{\text{constraints}_{t}}^{2} \cdot \|\boldsymbol{y}_{\text{constraints}_{t}} - \boldsymbol{\varPhi}_{\text{constraints}_{t}} \cdot \boldsymbol{x}\|_{2}^{2}}_{\text{regularization constraints and prior knowledge}} \right\},$$
 (7)

- 19 regularized by means of t=3 regularization terms, namely by horizontal and vertical smoothing constraints as well as by
- 20 prior knowledge from surface meteorology. Namely, the wet refractivity at the surface is computed from in-situ observations
- 21 of pressure, temperature, and dew point temperature at a single weather site within study area. As described in Heublein
- 22 et al. (2018), the horizontal smoothing constraints assuming the refractivity of a voxel (a,b,k) to equal the weighted mean
- 23 refractivity of the surrounding voxels (p,q,k) with voxel indices  $p \neq a$  and  $q \neq b$  within the same height layer k are defined
- 24 by:

25 
$$N_{\text{wet}_{a,b,k}} = \sum_{p,q} w_{p-a,q-b} \cdot N_{\text{wet}_{p,q,k}}$$
 (8)

1 The weights can e.g. be derived using inverse distance weighting

$$2 w_{p-a,q-b} = \begin{cases}
\frac{1}{d_{p-a,q-b}} & \text{if } (a,b) \neq (p,q) \\
\sum_{p,q} \frac{1}{d_{p-a,q-b}} & \text{if } (a,b) = (p,q), \\
-1 & \text{if } (a,b) = (p,q),
\end{cases}$$
(9)

- 3 with distances  $d_{p-a,q-b}$  between the center of voxel (p,q) and the center of voxel (a,b) of the considered kth height layer.
- 4 Moreover, Davis et al. (1993) state that an average refractivity profile can be approximated assuming the refractivity to expo-
- 5 nentially decrease with height:

6 
$$N_{\text{wet}}(h_k) = N_{\text{wet}}(h_0) \cdot \exp\left(-\frac{h_k - h_0}{H_{\text{scale}}}\right)$$
 (10)

- 7 The variable  $h_k$  is the height of the kth layer,  $h_0$  stands for some reference height at which the refractivity equals  $N_{\text{wet}}(h_0)$ , and
- 8  $H_{\text{scale}}$  represents the scale height of the local troposphere. As  $H_{\text{scale}}$  is essential for defining an exponential decay with height,
- 9 its value is determined within the solution of the tomographic system from a set of realistic values for  $H_{\rm scale}$  between 1000 m
- 10 and 2000 m. Both the weights for the horizontal and vertical smoothing constraints and for the prior knowledge from surface
- 11 meteorology are determined w.r.t. the data fidelity term using the place holder trade-off parameter  $\Gamma_{constraint}^2$  in Equation 7.
- 12 The selection of the trade-off parameters from a certain number of logarithmically scaled possible trade-off parameters and the
- 13 selection of  $H_{\rm scale}$  are described in Heublein et al. (2018) and Heublein (2019).
- 14 When aiming at a tomographic reconstruction of atmospheric water vapor by means of Compressive Sensing, the parameters
- 15 x are sparsely represented in some transform domain

16 
$$x = \Psi \cdot s$$
 (11)

17 as sparse parameters s. Estimates  $\hat{s}$  for these sparse parameters are obtained by

18 
$$\hat{s} = \underset{s}{\operatorname{argmin}} \left\{ \underbrace{\| \boldsymbol{y} - \boldsymbol{\Phi} \cdot \boldsymbol{\Psi} \cdot \boldsymbol{s} \|_{2}^{2}}_{\text{data fidelity term}} + \underbrace{\Gamma_{\text{CS}}^{2} \cdot \| \boldsymbol{s} \|_{1}}_{\text{L}_{1}-\text{norm regularization}} + \underbrace{\Gamma_{\text{constraints}}^{2} \cdot \| \boldsymbol{y}_{\text{constraints}} - \boldsymbol{\varPhi}_{\text{constraints}} \cdot \boldsymbol{\Psi} \cdot \boldsymbol{s} \|_{2}^{2}}_{\text{prior knowledge from surface meteorology}} \right\}$$
 (12)

- 19 as described in Heublein et al. (2018) and Heublein (2019). Instead of adding horizontal and vertical constraints to the data
- 20 fidelity term as in Equation 7, an  $L_1$ -norm regularization term is introduced in the CS solution to promote sparse solutions for
- 21 s, as described in Heublein et al. (2018) and Heublein (2019). The  $L_1$ -norm minimization of the sparse parameters reduces the
- 22 solution space. The wet refractivity estimates  $\hat{x}$  are then reconstructed using

23 
$$\hat{x} = \Psi \cdot \hat{s}$$
 (13)

- 24 with a dictionary  $\Psi \in \mathbb{R}^{L \times M}$ . As in Heublein et al. (2018) and Heublein (2019), the dimension M of the parameters  $s \in \mathbb{R}^{M \times 1}$
- 25 in the transform domain varies with the number of base functions resp. atoms in  $\Psi$ . Similarly to Heublein et al. (2018) and

Heublein (2019), we assert that a sparse representation of the refractivity distribution can be obtained by means of e.g. a 1 dictionary composed of Kronecker products of inverse Discrete Cosine Transform (iDCT) letters in longitude and latitude 2 3 directions and of Euler letters and Dirac letters in the height direction. When thinking of languages, an atom would stand for a word within a dictionary. Comparably to a word composed of different letters within a language dictionary, each atom results from the Kronecker product of smaller items, namely letters, within the dictionary for sparse representation. I.e., for 5 6 each column, i.e. line, of the three-dimensional (3D) wet refractivity signal, a Kronecker product of the one-dimensional (1D) letters along the longitude, latitude, and height direction are computed. In the longitude and latitude directions, iDCT letters 8 shall represent horizontal refractivity variations. The Euler letters model an exponential refractivity decay with height, and the 9 Dirac letters describe deviations from a decay described by a linear combination of Euler letters.

#### 3.3 Characteristics of study area and observing geometry settings

10

24

25

26

27

28 29

30

31

32

11 In Section 4, tomographic solutions obtained based on a high number of different observing geometry settings are compared. 12 The observing geometry settings result from i) a fixed voxel discretization, ii) seven to 32 sites, iii) five to 20 signal directions per site, and iv) 48 signal direction samples per number of sites and signals. Champollion et al. (2004) recommends i) horizontal 13 14 voxel sizes for a LSQ solution to water vapor tomography greater than or equal to the mean inter-site distance between the available GNSS sites, i.e. voxel sizes greater than or equal to about  $37 \times 37 \,\mathrm{km}^2$  resp. to about  $17 \times 17 \,\mathrm{km}^2$  in the case of seven 15 resp. 32 uniformly distributed GNSS sites within the investigated study area of about  $95 \times 99 \,\mathrm{km}^2$  size. In this work, the study 16 area is discretized into  $5 \times 5 \times 5$  voxels of horizontal sizes of about  $19 \times 20 \,\mathrm{km}^2$ . In the vertical direction, five height layers 17 are distinguished. With increasing height, the height layer thicknesses increase from 1300 m up to 2900 m. The lowest layer's 18 thickness is set to 1300 m in order to ensure at least for signals with very low elevation angles that a signal arriving at the 19 center of a voxel is able to pass the horizontally neighboring voxel within the same height layer. This is only possible if the 20 minimum thickness  $\Delta h_{\min}$  of the height layers is related to the horizontal voxel size  $\Delta hz = 20\,\mathrm{km}$  and to the cutoff elevation 21 angle  $\epsilon_{\rm cut} = 7^{\circ}$  by means of 22

23 
$$\Delta h_{\min} = \frac{1}{2} \cdot \Delta hz \cdot \tan \epsilon_{\text{cut}}.$$
 (14)

The ii) minimum number of seven sites originates from the real GNSS Upper Rhine Graben (URG) network site distribution within the analyzed study area. The maximum number of sites is chosen such that the rule of thumb of Champollion et al. (2004), introduced in Section 2, is clearly fulfilled. The horizontal position of the synthetic GNSS sites corresponds, for seven sites, to the position of real GNSS sites within the analyzed study area. The horizontal position of the additionally defined synthetic GNSS sites is chosen such that they are uniformly distributed within the study area. The vertical position of the synthetic GNSS sites corresponds to the height of the WRF digital elevation model at the horizontal position of the sites. The iii) number of signal directions per site is motivated by the GPS resp. by a multi-GNSS orbit geometry. According to Feairheller and Clark (2006), the Global'naya Navigatsionnaya Sputnikova Sistema (GLONASS) constellation disposes of 21 active plus three spare satellites on three orbital planes inclined by 64.8° w.r.t. the equator. In contrast, Hofmann-Wellenhof et al. (2008) describe the GPS orbit constellation to consist of 21 satellites plus three spares on six orbital planes inclined by 55° w.r.t. the

equator, and the Galileo orbit constellation to contain 27 operational plus three spare satellites on three planes inclined by 56° 1 w.r.t. the equator. Therefore, five signal directions resp. five visible satellites correspond to a pessimistic GPS setting e.g. with 2 3 site specific shadowing. Eight signal directions per site are here considered as a typical GPS setting at a GNSS permanent site (there may even be up to twelve observations for GPS-only), at which about 30% of the total number of GPS satellites is visible at a time. Similarly, a total number of 20 signal directions per site corresponds to a visibility of about 30% of the 5 6 total number of satellites at a time within a multi-GNSS constellation composed of GPS, GLONASS, and Galileo. Similarly, observation of the BeiDou Navigation Satellite System could also be used in order to increase the number of signal directions 8 in tomography applications. For each of the mentioned numbers of sites and numbers of visible satellites, 48 signal direction 9 samples are defined. Given the GPS repeat cycle of about one day, the number of 48 signal direction samples is chosen in order to emulate about half-hourly orbit samples. Using the orbit characteristics mentioned above, such synthetic half-hourly 10 satellite positions are approximated by means of circular orbits. 11

For each of the described observing geometry settings, synthetic SWD observations as input for the tomographic system are deduced from one single WRF simulation covering an about  $200\,\mathrm{km} \times 200\,\mathrm{km}$  large area centered around the longitude and latitude  $(\lambda,\varphi)=(8.15^\circ,49.15^\circ)$  at a  $900\,\mathrm{m}$  horizontal resolution. The vertical resolution increases with height, ranging from about  $50\,\mathrm{m}$  to about  $500\,\mathrm{m}$ . As schematically illustrated in Figure 1, for each synthetic GNSS site, this is done by means of averaging the refractivity information of all WRF cells situated within the defined tomographic voxels, a direct raytracing within these tomographic voxels, and adding together the SWD along each signal direction within the tomographic voxels using Equation 3. As the voxels are limited by ellipsoidal upper and lower borders, the raytracing is performed according to Perler (2011).

The horizontal distribution of the synthetic GNSS sites within the URG study area is shown in Figure 2. The signal directions result from selecting at random the defined number of signal directions from a synthetic multi-GNSS orbit constellation composed of GPS, GLONASS, and Galileo. Both signals entering the study area on its top and on its side are included.

From WRF, simulations of water vapor mixing ratio, temperature, pressure, and geopotential height are available at a  $900 \,\mathrm{m}$  horizontal resolution for generating the synthetic GNSS SWDs within the  $95 \times 99 \,\mathrm{km}^2$  large study area situated in the URG as shown in Figure 2. The topography within the Rhine Valley is flat. Height differences mainly occur at the foot of the Black Forest mountain range. The height difference between the highest and the lowest synthetic GNSS site used for this study is about  $494 \,\mathrm{m}$ .

## 4 Results

12 13

14

15


16

17 18


19

28

For the most humid acquisition date (27 June 2005) for which WRF simulations were provided for this research and for an exemplary voxel in the lower middle of the lowest voxel layer, Figure 3 shows that variations in the SWD signal directions available within the tomographic system cause variations in the estimated refractivities. The magnitude of the absolute wet refractivity values during the analyzed weather conditions ranges from 0 ppm to 74 ppm. As variations in the signal directions imply a change in the observed atmospheric volume, these variations in the estimated refractivities seem obvious. Yet,



**Figure 1.** Schematic illustration of the generation of synthetic GNSS SWDs according to Heublein (2019): Within each tomographic voxel (grey), the WRF refractivities of all those WRF cells (blue) situated within that voxel are averaged. A direct raytracing along the considered signal direction then yields the SWD introduced into the tomographic system.



**Figure 2.** Distribution of the seven GNSS permanent sites (blue squares) as well as of the five to 25 additional, synthetic sites (black symbols) within the URG study area. The additional, synthetic sites are distributed within a grid that uniformly covers the study area. Triangles, pentagons, hexagons, diamonds, and circles represent the first, second, third, fourth, and fifth group of five additional sites each.

Figure 3 illustrates that the variations in the refractivity estimates vary with the selected solution strategy. When considering 1 many sites and many signal directions per site (e.g. at least 27 sites and at least 15 signal directions), the difference between 2 the CS refractivity estimates and the WRF refractivity of the considered voxel approaches zero for most samples. However, 3 e.g. for 27 sites and 20 signal directions per site, there are some samples in which the CS based refractivity estimate differs from the WRF refractivity by up to 3.3 ppm. I.e. for many signal directions, CS is able to accurately and precisely reconstruct 5 6 the voxel's refractivity, but for some signal directions, the voxel's refractivity estimate does not match well with the voxel's validation refractivity from WRF. In contrast, in the case of few sites and few signal directions per site (e.g. twelve sites and 8 ten signal directions per site), LSQ yields refractivity estimates differing from -5.9 ppm to -0.7 ppm from the WRF refractiv-9 ity, while the CS refractivity estimates differ much more from the WRF refractivity (differences of  $-42.9 \,\mathrm{ppm}$  to  $26.9 \,\mathrm{ppm}$ ). Consequently, when investigating the observing geometry's effect on the quality of the tomographic reconstruction, the chosen 10 solution strategy as well as the effect of varying signal directions should be taken into account. Therefore, in this research, a representative set of 48 half-hourly samples of synthetic GNSS orbits is considered in order to analyze the observing geome-12 13 try's effect on the tomographic reconstruction quality.

14 15

16

17

18 19

20 21

22 23

24 25

26 27

28

29

30 31

32

33

34

35

11

As expected, an increased number of sites and an increased number of signal directions per site, in general, decrease the mean of the absolute difference (called mean difference in the following) and the standard deviation of the difference between estimated refractivities and WRF refractivities. Yet, as shown in Figure 4 averaged over all voxels, in the case of a LSQ solution to the tomographic system, the mean difference decrease by means of introducing more SWD estimates into the tomographic reconstruction is much smaller than that in the case of a CS solution. When averaged over 48 samples per observing geometry, introducing more SWD estimates improves the mean difference by up to 1.3 ppm resp. 1.9 ppm (maximum improvement observed for 20 resp. 15 signal directions per site in the case of LSQ resp. CS).

A more in-depth analysis does not show any significant differences among the individual voxels. Moreover, no significant systematics between the LSQ and CS solutions appeared, neither at the boundary layer nor at the top of the atmosphere. For most of the tested scenarios, LSO provides better results than CS. However, if there are many sites and many different signal directions available, CS yields more accurate and more precise results than LSQ.

When investigating the standard deviation of the differences between estimated refractivities and WRF refractivities for the CS case, considering an increased number of synthetic GNSS sites only, while keeping a constant number of five signal directions per site, is not advantageous. However, as of 15 different signal directions per site, a clear improvement in standard deviation is visible when increasing the number of sites in the tomographic setting solved by means of CS. Independently of the number of sites, for realistic GPS-like observing geometry settings with five to ten signal directions per site, the LSO refractivity estimates are more precise than the CS refractivity estimates. In contrast, as of 15 signal directions per site, the CS solution yields more accurate and more precise refractivity estimates than the LSQ solution if at least 22 sites are available. I.e. this study shows that LSO is less sensitive to the number of signal directions than CS. Therefore, we recommend to use LSO for water vapor tomography disposing of GPS-only observations and CS for water vapor tomography disposing of multi-GNSS SWD





Figure 3. Absolute differences between estimated refractivity and the WRF refractivity in ppm for an exemplary voxel in the lower middle of the lowest voxel layer for the 48 samples of each investigated observing geometry setting. The two left columns dispose of an ordinate ranging from  $-25 \,\mathrm{ppm}$  to  $25 \,\mathrm{ppm}$ , the third column plots the differences within the range  $-10 \,\mathrm{ppm}$  to  $10 \,\mathrm{ppm}$ , and the right column plots the differences within the range  $-5 \,\mathrm{ppm}$  to  $5 \,\mathrm{ppm}$ . The legend in the upper left subplot holds for all subplots: red circles stand for LSQ results, while blue squares represent the CS results. In each subplot, the minimum and maximum absolute differences in ppm of the LSQ resp. CS refractivity estimate w.r.t. the WRF input refractivities and the mean and the standard deviation over all samples are given in red resp. blue. Moreover, the mean and the standard deviation over all samples are indicated, for LSQ by a red dashed line resp. for CS by a blue dashdotted line and by errorbars in the corresponding colors.



**Figure 4.** Averaged over all voxels, this figure shows the mean of the absolute difference and the std of the difference between estimated refractivities and WRF refractivities in ppm, deduced from 48 samples of each investigated observing geometry setting composed of a certain number of synthetic GNSS sites and various numbers of signal directions per site. The dashed resp. dotted lines serve for better following the variation of the represented quantities with the number of sites, but only the discrete values indicated by the markers should be evaluated. The legend in the upper left subplot holds for all subplots. In each subplot, the improvement by introducing 32 sites instead of seven sites is given in red resp. blue. Degradations are given with a minus sign.

estimates.

In the case of the maximum number of sites and the maximum number of signal directions per site (32 sites and 20 signal directions per site), when averaged over the 48 considered samples per observing geometry, the mean difference and the standard deviation of the LSQ resp. CS reconstruction attain values of about 0.3 ppm resp. 0.0 ppm. Therefore, the number of sites and the number of signal directions per site are of particular interest when aiming at a very accurate and very precise tomographic reconstruction using CS.

reconstruction using CS. For the given  $5 \times 5 \times 5$  voxel discretization with horizontal voxel sizes of  $19\,\mathrm{km}$  resp.  $20\,\mathrm{km}$ , the rule of thumb of Champollion et al. (2004) requests the mean inter site distance to correspond to no more than  $19\,\mathrm{km}$  to  $20\,\mathrm{km}$ . The results show that, using the investigated synthetic data set with and at least 15 signal directions per site, the CS solution is able to more accurately and more precisely reconstruct the atmospheric water vapor distribution than LSQ in the case of 22 sites within the  $95 \times 99\,\mathrm{km}^2$  large study area, i.e. at a site density of about one site per  $20.7 \times 20.7\,\mathrm{km}^2$  which is a bit lower than that required by the rule of thumb of Champollion et al. (2004). I.e. if 15 signal directions are available per site, the rule of thumb can be transferred from the LSQ solution to water vapor tomography to CS solutions.

Consequently, the following three main results are summarized from this study:

1. The rule of thumb of Champollion et al. (2004) can be transferred from LSQ to CS.

- 2. Based on site distributions obeying the rule of thumb of Champollion et al. (2004), CS needs a variety of at least 15 signal directions per site in order to estimate the 3D refractivity field more accurately and precisely than LSQ.
- 3. While LSQ seems to be less sensitive on the number of signal directions than CS. Therefore, CS should only be used in the case of multi-GNSS SWD estimates yielding a variety of at least 15 signal directions per site.

## 5 5 Discussion and outlook

6 Section 4 states that the rule of thumb of Champollion et al. (2004) does not only hold for a tomographic solution based on LSQ, but that it also ensures a good tomographic reconstruction in the case of a CS solution. Although this finding is based 7 8 on many different observing geometry settings, it only refers to a single voxel discretization and to a single study area with a single topography and a single site distribution within that study area. As a consequence, this research mainly investigates the 9 10 validity of the rule of thumb of Champollion et al. (2004) for CS for the given study area, weather condition, and voxel discretization. For generalization, further tests should be performed that repeat the described methodology for other study areas, 11 12 weather conditions, and voxel discretizations, and for site distributions varying not only in the number, but also in the position of the sites. In particular, using only five vertical layers potentially represents limits the validity of the results of the proposed 13 14 approach. 15 Moreover, as the presented approach only relies on a synthetic data set deduced from WRF, the synthetic SWDs introduced within the tomographic system in this research are too optimistic, when compared to real GNSS SWD estimates. Therefore, the 16 conclusions drawn in Section 4 cannot necessarily be transferred to tomographic applications involving real SWD estimates. 17 In order to get a better idea on the transferability of the results, the analysis should be repeated based on real data, or the effect 18 of adding different types of noise to the synthetic SWD estimates should be investigated (e.g. measurement and sensor noise 19 and uncertainties resulting from the observing geometry). In the presented approach, instead of mapping ZWDs (Zenith Wet 20 21 Delays, related to SWDs by means of mapping as described e.g. in Niell (1996)) to the slant signal directions as in the case of a real GNSS processing, the synthetic SWD data set is computed based on a direct raytracing within the same voxels in which 22 23 the tomographic reconstruction is thereafter performed. Yet, Heublein (2019) shows that this involves neglecting both a voxel 24 discretization error and a mapping error committed in the case of real data. 25 Furthermore, Section 4 shows that the standard deviation of the difference between LSQ refractivity estimates and WRF refractivities is 6% to 65% smaller than that computed based on the CS refractivity estimates, if at most ten different signal 26 27 directions per site are available. In contrast, in the case of a high number of sites and a high number of signal directions per site, the LSQ reconstruction is not able to yield as accurate and as precise estimates of the water vapor distribution as CS. 28 29 I.e. when solving the tomographic system by means of LSQ, increasing the number of SWD signal directions improves the 30 tomographic reconstruction quality less than when using CS. This may be due to the geometric smoothing constraints forming the basis of the LSQ solution. In the case of a small number of observations, the smoothing constraints ensure a smooth solu-31 32 tion free of outliers that does not necessarily correspond to the prevailing atmospheric conditions. In the case of a high variety 33 of observations, the smoothing constraints become less important w.r.t. the data fidelity term within the LSO solution to the

- 1 tomographic system, but they still effect the tomographic solution. Even in the case of a very high number of observations, the
- 2 tomographic system cannot be solved in a pure data-driven way. Instead, the tomographic solution always takes into account
- 3 to the chosen model assumptions, i.e. the LSQ solution always applies a certain amount of smoothing.
- 4 In addition, a low resp. a high number of signal directions chosen from a synthetic multi-GNSS constellation for the recom-
- 5 mendation of LSQ resp. CS for GPS-only resp. for multi-GNSS water vapor tomography applications should not be to set
- 6 equal to considering a real GPS-only resp. a real multi-GNSS setting. Choosing a small number of signal directions from a
- 7 multi-GNSS constellation yields a higher variability in the signal directions than choosing the same small number of signal
- 8 directions from a GPS-only constellation. Since a high number of signal directions showed to be of particular importance in
- 9 the case of a CS solution, the quality of the refractivity estimates deduced using CS may decrease, if real GPS-only signal
- 10 directions are chosen.
- 11 Finally, future research should analyze in more detail which signal directions are necessary in a LSQ resp. CS based water
- 12 vapor tomography in order to well reconstruct the refractivities of as much voxels as possible. A two-step CS LSQ may then
- 13 first yield accurate refractivity estimates for most voxels by means of CS and then use the geometric smoothing constraints
- 14 applied in LSQ to improve the refractivity estimates of those voxels in which CS yields inaccurate refractivity estimates even
- 15 if a high number of sites and a high number of signal directions per site are available.
- 16 Author contributions. Marion Heublein developed the theory and performed the computations. Patrick Erik Bradley and Stefan Hinz verified
- 17 the analytical methods and supervised the findings of Marion Heubleins work.
- 18 Competing interests. Within the last years, Marion Heublein and Stefan Hinz collaborated with the Signal Processing in Earth Observation
- 19 (SiPEO) team of the German Aerospace Center and with Giovanni Nico (Consiglio Nazionale delle Ricerche Bari, Italy) and Pedro Benevides
- 20 (University of Lisbon, Portugal).
- 21 Acknowledgements. The first author was supported by a scholarship of the Deutsche Telekom Stiftung. Thanks to Franz Ulmer (formerly at
- 22 the German Aerospace Center at the Remote Sensing Technology Institute) for providing WRF data. The authors acknowledge support by
- 23 the KIT-Publication Fund of the Karlsruhe Institute of Technology.

#### 1 References

- 2 Aguilera, E., Nannini, M., and Reigber, A.: A data-adaptive compressed sensing approach to polarimetric SAR tomography of forested areas,
- 3 IEEE Geoscience and Remote Sensing Letters, 10, 543–547, 2013.
- 4 Alonso, M. T., López-Dekker, P., and Mallorquí, J. J.: A novel strategy for radar imaging based on compressive sensing, IEEE Transactions
- 5 on Geoscience and Remote Sensing, 48, 4285–4295, 2010.
- 6 Baraniuk, R.: Compressive sensing, IEEE signal processing magazine, 24, 2007.
- 7 Bender, M. and Raabe, A.: Preconditions to ground based GPS water vapour tomography, in: Annales Geophysicae, vol. 25, pp. 1727–1734,
- 8 Copernicus GmbH, 2007.
- 9 Bender, M., Dick, G., Wickert, J., Ramatschi, M., Ge, M., Gendt, G., Rothacher, M., Raabe, A., and Tetzlaff, G.: Estimates of the information
- 10 provided by GPS slant data observed in Germany regarding tomographic applications, Journal of Geophysical Research: Atmospheres,
- 11 114, 2009.
- 12 Bender, M., Dick, G., Ge, M., Deng, Z., Wickert, J., Kahle, H.-G., Raabe, A., and Tetzlaff, G.: Development of a
- 13 GNSS water vapour tomography system using algebraic reconstruction techniques, Advances in Space Research, 47, 1704 –
- 14 1720, https://doi.org/http://dx.doi.org/10.1016/j.asr.2010.05.034, http://www.sciencedirect.com/science/article/pii/S0273117710003790,
- 15 {GNSS} Remote Sensing-2, 2011a.
- 16 Bender, M., Stosius, R., Zus, F., Dick, G., Wickert, J., and Raabe, A.: GNSS water vapour tomography–Expected improvements by combining
- 17 GPS, GLONASS and Galileo observations, Advances in Space Research, 47, 886–897, 2011b.
- 18 Budillon, A., Evangelista, A., and Schirinzi, G.: Three-dimensional SAR focusing from multipass signals using compressive sampling, IEEE
- 19 Transactions on Geoscience and Remote Sensing, 49, 488–499, 2011.
- 20 Candès, E. J. and Wakin, M. B.: An introduction to compressive sampling, Signal Processing Magazine, IEEE, 25, 21–30, 2008.
- 21 Candès, E. J. et al.: Compressive sampling, in: Proceedings of the international congress of mathematicians, vol. 3, pp. 1433–1452, Madrid,
- 22 Spain, 2006.
- 23 Champollion, C., Masson, F., Bouin, M.-N., Walpersdorf, A., Doerflinger, E., Bock, O., and Van Baelen, J.: GPS water vapour tomography:
- preliminary results from the ESCOMPTE field experiment, Atmospheric research, 74, 253–274, 2004.
- 25 Davis, J. L., Elgered, G., Niell, A. E., and Kuehn, C. E.: Ground-based measurement of gradients in the "wet" radio refractivity of air, Radio
- 26 Science, 28, 1003–1018, 1993.
- 27 Ding, N., Zhang, S., Wu, S., Wang, X., Kealy, A., and Zhang, K.: A new approach for GNSS tomography from a few GNSS stations,
- Atmospheric Measurement Techniques, 11, 3511–3522, 2018.
- 29 Donoho, D. L.: Compressed sensing, IEEE Transactions on Information Theory, 52, 1289–1306, 2006.
- 30 Elosegui, P., Ruis, A., Davis, J., Ruffini, G., Keihm, S., Bürki, B., and Kruse, L.: An experiment for estimation of the spatial and temporal vari-
- ations of water vapor using GPS data, Physics and Chemistry of the Earth, 23, 125 130, https://doi.org/http://dx.doi.org/10.1016/S0079-
- 32 1946(97)00254-1, http://www.sciencedirect.com/science/article/pii/S0079194697002541, 1998.
- 33 Feairheller, S. and Clark, R.: Other satellite navigation systems, Understanding GPS-principles and applications, 2nd edition. Artech House,
- 34 Norwood, pp. 595–634, 2006.
- 35 Flores, A., Ruffini, G., and Rius, A.: 4D tropospheric tomography using GPS slant wet delays, in: Annales Geophysicae, vol. 18, Springer,
- 36 2000.

- 1 Gradinarsky, L. P. and Jarlemark, P.: Ground-based GPS tomography of water vapor: Analysis of simulated and real data, Journal of the
- 2 Meteorological Society of Japan, 82, 551–560, 2004.
- 3 Grohnfeldt, C., Zhu, X. X., and Bamler, R.: Jointly sparse fusion of hyperspectral and multispectral imagery, in: Geoscience and Remote
- 4 Sensing Symposium (IGARSS), 2013 IEEE International, pp. 4090–4093, IEEE, 2013.
- 5 Hansen, M. H. and Yu, B.: Model selection and the principle of minimum description length, Journal of the American Statistical Association,
- 6 96, 746–774, 2001.
- 7 Heublein, M.: GNSS and InSAR based water vapor tomography: A Compressive Sensing solution, Ph.D. thesis, Karlsruhe Institute of
- 8 Technology (KIT), https://doi.org/10.5445/IR/1000093403, 2019.
- 9 Heublein, M., Alshawaf, F., Erdnüß, B., Zhu, X. X., and Hinz, S.: Compressive sensing reconstruction of 3D wet refractivity based on GNSS
- 10 and InSAR observations, Journal of Geodesy, https://doi.org/10.1007/s00190-018-1152-0, https://doi.org/10.1007/s00190-018-1152-0,
- 11 2018.
- 12 Hirahara, K.: Local GPS tropospheric tomography, Earth, Planets and Space, 52, 935–939, https://doi.org/10.1186/BF03352308, http://dx.
- doi.org/10.1186/BF03352308, 2000.
- 14 Hofmann-Wellenhof, B., Lichtenegger, H., and Wasle, E.: GNSS Global Navigation Satellite Systems: GPS, GLONASS, Galileo and
- more, Springer, Wien, http://swbplus.bsz-bw.de/bsz275454096cov.htm, 2008.
- 16 Hurter, F. and Maier, O.: Tropospheric profiles of wet refractivity and humidity from the combination of remote sensing data sets and
- measurements on the ground, Atmospheric Measurement Techniques, 6, 3083–3098, 2013.
- 18 Jiang, C., Zhang, H., Shen, H., and Zhang, L.: Two-step sparse coding for the pan-sharpening of remote sensing images, IEEE Journal of
- 19 Selected Topics in Applied Earth Observations and Remote Sensing, 7, 1792–1805, 2014.
- 20 Li, S. and Yang, B.: A new pan-sharpening method using a compressed sensing technique, IEEE Transactions on Geoscience and Remote
- 21 Sensing, 49, 738–746, 2011.
- 22 Niell, A.: Global mapping functions for the atmosphere delay at radio wavelengths, Journal of Geophysical Research: Solid Earth, 101,
- 23 3227-3246, 1996.
- 24 Nilsson, T. and Elgered, G.: Water vapour tomography using GPS phase observations: Results from the ESCOMPTE experiment, Tellus A:
- 25 Dynamic Meteorology and Oceanography, 59, 674–682, 2007.
- 26 Notarpietro, R., Gabella, M., and Perona, G.: Tomographic reconstruction of neutral atmospheres using slant and horizontal wet delays
- achievable through the processing of signal observed from small GPS networks, Ital. J. Remote Sens, 40, 63–74, 2008.
- 28 Perler, D.: Water vapor tomography using global navigation satellite systems, Ph.D. thesis, Diss., Eidgenössische Technische Hochschule
- 29 ETH Zürich, Nr. 20012, 2011, 2011.
- 30 Potter, L. C., Ertin, E., Parker, J. T., and Cetin, M.: Sparsity and compressed sensing in radar imaging, Proceedings of the IEEE, 98, 1006-
- 31 1020, 2010.
- 32 Pruente, L.: Application of compressed sensing to SAR/GMTI-data, in: Synthetic Aperture Radar (EUSAR), 2010 8th European Conference
- on, pp. 1–4, VDE, 2010.
- 34 Rauhut, H.: Compressive sensing and structured random matrices, Theoretical foundations and numerical methods for sparse recovery, 9,
- 35 1–92, 2010.
- 36 Rohm, W.: The precision of humidity in {GNSS} tomography, Atmospheric Research, 107, 69 75,
- 37 https://doi.org/http://dx.doi.org/10.1016/j.atmosres.2011.12.008, http://www.sciencedirect.com/science/article/pii/S0169809511004194,
- 38 2012.

- 1 Rohm, W.: The ground GNSS tomography–unconstrained approach, Advances in Space Research, 51, 501–513, 2013.
- 2 Rohm, W., Zhang, K., and Bosy, J.: Limited constraint, robust Kalman filtering for GNSS troposphere tomography, Atmospheric Measure-
- 3 ment Techniques, 7, 1475–1486, 2014.
- 4 Skamarock, W. C., Klemp, J. B., Dudhia, J., Gill, D. O., Barker, D. M., Wang, W., and Powers, J. G.: A description of the advanced research
- 5 WRF version 2, Tech. rep., National Center For Atmospheric Research Boulder Co Mesoscale and Microscale Meteorology Div, 2005.
- 6 Song, S., Zhu, W., Ding, J., and Peng, J.: 3D water-vapor tomography with Shanghai GPS network to improve forecasted moisture field,
- 7 Chinese Science Bulletin, 51, 607–614, https://doi.org/10.1007/s11434-006-0607-5, http://dx.doi.org/10.1007/s11434-006-0607-5, 2006.
- 8 Troller, M.: GPS based determination of the integrated and spatially distributed water vapor in the troposphere, vol. 67, 2004.
- 9 Xia, P., Cai, C., and Liu, Z.: GNSS troposphere tomography based on two-step reconstructions using GPS observations and COSMIC profiles,
- in: Annales Geophysicae, vol. 31, 2013.
- 11 Zhao, Q., Yao, Y., Cao, X., and Yao, W.: Accuracy and reliability of tropospheric wet refractivity tomography with GPS, BDS, and GLONASS
- observations, Advances in Space Research, 63, 2836–2847, 2019.
- 13 Zhu, X. X. and Bamler, R.: Tomographic SAR inversion by  $L_1$ -norm regularization The compressive sensing approach, IEEE Transactions
- on Geoscience and Remote Sensing, 48, 3839–3846, 2010.
- 15 Zhu, X. X. and Bamler, R.: A sparse image fusion algorithm with application to pan-sharpening, Geoscience and Remote Sensing, IEEE
- 16 Transactions on, 51, 2827–2836, 2013.
- 17 Zhu, X. X. and Bamler, R.: Superresolving SAR tomography for multidimensional imaging of urban areas: Compressive sensing-based
- TomoSAR inversion, IEEE Signal Processing Magazine, 31, 51–58, 2014.
- 19 Zhu, X. X., Grohnfeldt, C., and Bamler, R.: Exploiting joint sparsity for pansharpening: The J-SparseFI algorithm, IEEE Transactions on
- 20 Geoscience and Remote Sensing, 54, 2664–2681, 2016.